Journal of Nonlinear Analysis and Optimization Vol. 14, Issue. 2 : 2023 ISSN : **1906-9685** 



# Solution based on MIMO-OFDM and Space-Time Shift Keying (STSK)

Dr.G.Jyoshna, Assistant Professor, Dept. of E.C.E ,SKU College of Engineering and Technology, S.K. University Ananthapur-515003

Abstract—Next generation wireless standards will exploit the wide bandwidth available at the millimeter-wave (mm-Wave) frequencies, in particular the E-band (71-76 GHz and 81-86 GHz). This large available bandwidth may be converted into multi-gigabit capacity, when efficient and computationally-affordable transceivers are designed to cope with the constrained power budget, the clustered fading and the high level of phase noise, which actually characterize mm-wave connections. In this paper, we propose a viable Multiple-Input Multiple-Output (MIMO) solution for high bitrate transmission in the E-band with application to small-cell backhaul based on Space-Time Shift Keying (STSK) and Orthogonal Frequency Division Multiplexing (OFDM). STSK provides an efficient trade-off between diversity and multiplexing without inter-channel interference (ICI) and without the need for large antenna arrays. These features make STSK theoretically preferable over other throughputoriented space-time coding techniques, namely Spatial Multiplexing (SMUX) and Spatial Modulation (SM), which were recently considered in the literature for mm-wave MIMO applications. In this paper we consider the most significant channel impairments related to small-cell backhaul in dense urban environment, namely the correlated fading with and without the presence the line-ofsight (LOS), the phase noise, the rain attenuation and shadowing. Additionally, we consider smallsize MIMO systems ( $2 \times 2$  and  $4 \times 4$ ), and low-cost base station equipments in the perspective of easily-deployable small-cell network components. Comparative results, obtained by intensive simulations targeted at assessing link performance and coverage, have clearly shown the superior performance of STSK against counterpart techniques, although obtained at the cost of a somewhat reduced spectral efficiency.

*Index Terms*—Millimeter wave communications, MIMO, OFDM, Space-time coding, Space-Time Shift Keying, Small cells, Wireless backhaul, 5G.

# I. Introduction

As stated in [1], the key essence of 5G wireless networks lies in exploring the unused high frequency millimeter-wave (mm-wave) bands, formally ranging from 3 to 300 GHz. Even a small fraction of the available mmwave spectrum can support data rate that is hundred times that in current cellular spectrum.

Hence, the use of the E-band for short and medium range point-to-point terrestrial communications has been recently considered worldwide [2]. For example, the Federal Communications Commission (FCC) has regulated the use of frequencies at E-band from 71 GHz to 76 GHz, from 81 GHz to 86 GHz and from 92 GHz to 95

GHz to licensed users in 2003. In Europe, the Electronic Communication Committee (ECC) has recommended through the ECC/REC (05)/07 such frequency bands for broadband fixed radio link applications. A document issued in 2008 by the Ministry of Economic Development of Australia contains some preliminary regulations on the usage of E-bands for terrestrial wireless the communications. As alternative to the E-band, recent licensing process of the 28 GHz band pointed out the possibility of using the frequency range from 27.50 GHz to 28.35 GHz, which can be organized into two slots of 360 MHz each [3].

The rigorous and detailed experimental analysis of mm-wave propagation proposed in [4] estimated

achievable the capacity in dense urban environment both in the presence and absence of LOS, where sounders equipped with small-size antenna arrays of 4 and 8 elements have been used for practical tests in New York City. Results were shown for 73 GHz E-band compared to 28 GHz band, while considering the same channelisation of 500 MHz. The outcomes of the aforementioned analysis showed that the higher pathloss measured at 73 GHz limits the available cell-edge rate, which is approximately half of the capacity achieved in the 28 GHz band, while using the same number of antenna elements. However, using twice the number of antennas compared to 28 GHz allows the 73 GHz transmitters (Tx) to efficiently exploit MIMO spatial diversity without increasing the array size. Due to higher pathloss, NLOS mmwave link capacity significantly drops with respect to LOS one, but it is still 20 fold increased with respect to that of sub 6 GHz bands [4].

As reported in [4], MIMO techniques represent the first cornerstone of future multi-gigabit mmwave communications. The second cornerstone is represented by multicarrier modulations, where it was reported in [5] that the "*OFDM principle*", with each data packet made up of a number of complex-valued sinusoids that are modulated by information symbols, still represents the leading concept of waveform design in future 5G communications exploiting mm-wave frequencies.

The achievements of [4] suggest that MIMObased Eband connections could be profitably exploited for wireless backhaul of urban cells. For many years, cell backhaul has been exclusively managed by wired PSTNs and fiber links. However, with the progressive cell size reduction and the consequential increase of cells number, backhaul solutions had to become more cost effective, scalable and easy to install as compare to traditional macro backhaul technologies. Wellknown wired technologies do not seem to cope with such soaring requirements and hence 3GPP standardization committee proposed wireless solutions for small cell backhauling, which are based on LOS/NLOS microwave connections and LOS mm-wave connections [6]. The importance of wireless backhaul will increase significantly in 5G, where the cell size is expected to reduce further. Authors of [7] claim that in 5G ultra-dense

networks, the macrocell Base Station (BS) is configured only to transmit the management data for controlling the user handover in small cells and the small cell BS takes charge of the user data transmission. Therefore, the small cell network is not a complement for the macrocell network and hence it should be provided by autonomous backhauling capabilities that only dedicated wireless connections can fulfil.

Some past contributions preliminarily assessed the viability of mm-wave short-range connections, mainly in local networking applications. In [8], Dyadyuk et. al. developed a practical solution for LOS-based multigigabit point-to-point E-band transmission in the 81-86 GHz bandwidth. Such a solution is based on analogue Frequency Division Multiplexing (FDM) of the data stream, using rootraised cosine bandpass filters to shape the subchannels. Additionally, [9] can be regarded as an improvement of [8], where the same FDM-based solution of [8] was used in conjunction with MIMO Spatial Multiplexing and Low-Density-Parity Check (LDPC) coding to boost the capacity of short-range point-to-point mmwave LOS connections. Vertical-Bell Laboratories Layered Space-Time (VBLAST) technique [10] for successive interference cancellation has been used in [9] to reduce the impact of ICI on the receiver's (Rx) performance.

One of the early contributions about mm-wave small cell backhaul has been published in [11], where the authors showed that under LOS assumption and using MIMO multiplexing together with adaptive modulation and coding, it is possible to reach up to 10 Gb/s of backhaul capacity. Some more recent works inserted mmwave backhaul in the framework of 4G and 5G systems. Authors of [12] consider  $2 \times 2$  MIMO with spatial multiplexing for 28 GHz small-cell backhaul in 4G standards, where convolutional coded single-carrier M-ary QAM modulation has been used to transmit backhaul data. LOS-MIMO mm-wave backhaul exploiting Spatial Multiplexing was proposed in [13], where an array of  $1m \times 1m$  is used at the transmitter and receiver sides. Additionally, in order to improve the system's performance, while reducing baseband receiver complexity, Time-Hopping Impulse-Radio (TH-IR) transmission has been adopted in [14] for 81 GHz small-cell backhaul. In this work,

single antenna system has been considered along with the hypothesis of "*pencil-beam*" LOS propagation. Furthermore, the work reported in [15] and [16] aims at integrating small-cell backhaul in the framework of massive MIMO systems, which is expected to be one of the key technologies of 5G and will make easier backhaul in largescale and ultra-dense networks.

In this paper, we propose a practical system solution for small cell backhaul at mm-wave frequencies, based on MIMO and OFDM. The proposed solution relies on the use of Space-Time Shift Keying (STSK) in combination with maximum likelihood (ML) detection performed in the frequency domain. STSK is a space-time coding technique proposed to exploit the benefits of MIMO without the need for high-complexity detection algorithms [17]. STSK is a generalized shift-keying architecture utilizing both the space and time dimensions that is based on activation of indexed Q > 1 orthogonal space-time dispersion matrices within one symbol block duration. Due to such degrees of freedom, STSK is capable of striking a flexible diversity versus multiplexing gain trade-off, which is achieved by optimizing both the number and size of the dispersion matrices as well as the number of transmit and receive antennas. STSK can be regarded as an improvement state-of-the-art of MIMO multiplexing techniques, namely the Spatial Multiplexing (SMUX) and the Spatial Modulation (SM) [18]. SMUX, adopted by the largest part of state-of-the-art contributions dealing with small cell backhaul, multiplexes a number of symbols in space domain such that the different symbol streams overlap over the MIMO channel. As a result, inter-channel interference (ICI) arises and must be dealt with at the receiver side using computationally intensive processing that becomes prohibitive for high number of antennas N. On the other hand, SM has been proposed in order to exploit the benefits of MIMO multiplexing, while reducing the required receiver complexity. SM activates only one transmit antenna for each symbol period, while the other N-1 antennas remain silent. Therefore, in SM the ICI is avoided and optimum symbol detection can be implemented with affordable computational complexity. However, the multiplexing gain of SM is dramatically reduced with respect to SMUX. A

simplified version of SM is Space-Shift Keying (SSK), which was proposed in [19] for E-band LOS backhaul applications. In SSK, the *i*th symbol is univocally individuated by the *i*-th activated antenna. Despite the reduced complexity of the detection and favourable BER performance achieved, SSK fails to provide an acceptable throughput when small-size MIMOs are used. On the other hand, STSK has the capability to increase the multiplexing gain by increasing the number of dispersion matrices without increasing the number of antennas.

The advantages of STSK make is suitable for future multi-gigabit mm-wave communications, in particular when small cell backhaul in dense urban scenarios is considered. Indeed, the mm-wave propagation in dense urban environment actually presents some challenging aspects, where it was shown in [4] that besides LOS and NLOS the mmwave channel exhibits a third outage state, where signal-to-noise ratio (SNR) at the receiver is approaching  $-\infty$  dB. This is due to the fact the path loss, in either LOS or NLOS state, is sufficiently large to drop the SNR below any acceptable threshold. In [4] a three-state probabilistic channel model is proposed in order to take into account the outage situation. Such a model is based on the of LOS, computation NLOS and outage probabilities, which substantially depends on the transmitter's and receiver's antenna distance and the surrounding environment. On the basis of this model, the probability of NLOS channel state significantly increases with the antenna distance. Under these critical propagation conditions, the available power resources may be severely limited and robust transmission solutions should be envisaged.

Small-cell backhaul application is particularly critical, where it is characterized by stringent requirements in terms of low bit-error-rate ( $\leq 10^{-6}$ ) and high availability (possibly 99.999% or "five 9s"). Therefore, transmission robustness is the first issue to be addressed followed by throughput analysis, because the data rate of backhaul network should be high enough to convey information with minimum latency. Therefore, in this paper we consider STSK-OFDM as a valuable solution to support mm-wave small-cell backhaul in highlycritical and potentially-hostile metropolitan scenarios.

The common factor of most of related state-oftheart contributions is the assumption of *free-space* LOS propagation regarded as necessary condition in order to guarantee backhaul connectivity, while different propagation modalities are generally assumed as "*outage*". However, the presence of free-space LOS between base stations cannot be realistically assumed by default in small cell urban scenarios. In such a framework, STSK can offer an efficient trade-off between MIMO diversity and multiplexing, allowing to configure the backhaul system in a way to improve link performance, while also achieving a satisfactory data throughput.

The rest of the paper is structured as follows. Section II will consider requirements and constraints of mmwave small cell backhaul, Section III covers the mmwave MIMO-STSK backhaul system with OFDM transmission. Section IV analyzes the mm-wave channel in the urban scenarios considered for small-cell backhaul. Section V discusses selected simulation results in terms of link performance and coverage. Finally, conclusions are drawn in Section VI.

II. Requirements and constraints of small-cell wireless backhaul

Traffic generated inside a cell is transported to the core network using the backhaul and hence the availability of the backhaul links is essential to guarantee the required throughput inside a cell. Some essential requirements on small-cell backhaul are listed as follows [20]:

- To support the traffic originated in each cell on the scale of hundreds of Mbps;
- To support NLOS connections;
- To connect tens of small cells in an area of few kilometers, assuming that small cells are deployed with spacing 30 to 300 m;
- To minimize the latency up-to submillisecond.

Unlike access, continuous link availability is essential for backhaul. For example 4G/LTE-A requirements point out very high link availability of "*five 9s*" at BER less than or, at most, equal to  $10^{-6}$  [21]. Such a claim is contradicted by the application note of Ceragon corp. (Palo Alto, CA) [22], where it is stated that "*five 9s*" availability is not strictly required for small-cell backhaul. Their motivation is that small cells form an offload underlay to a higher-availability macrocell. The

exploitation of E-band frequencies for small-cell backhaul would allow in principle to cope with the broadband connectivity requirements listed above. The use of robust MIMO spacetime coded transmission should enhance link availability and coverage under critical NLOS propagation conditions typical of 5G urban scenarios.

In Fig. 1 we depict the dense-urban backhaul scenario considered in our work, where some small transceiver base stations offering connectivity to small-cell users are mounted on street poles. The height of street poles in US is 8 meters, so it is reasonable to suppose that BS equipment is placed 6-7 meters from the ground level. On the other hand, the "macro BS" representing the main node of the backhaul network is placed on the rooftop of a tall building of 20 meters height. Fixed and mobile potential obstructions due to buildings and other elements are present between transmit and receive antennas, which would affect the propagation characteristics such that the presence of LOS backhaul cannot be guaranteed a priori. for long distances, the outage Moreover, occurrence should also be considered. For these reasons, the three-state channel modelling proposed in [4] are considered appropriate to describe large scale and small scale propagation impairments characterising the scenario drawn in Fig. 1. In Section IV, the detailed channel modelling concerning the considered backhaul application will be provided.

III. STSK MIMO-OFDM system for mm-wave small-cell backhaul

A. Introduction to STSK and comparison with other space-time coding techniques

Space-Time Shift Keying (STSK) technique is a generalized shift-keying architecture utilizing both the space and time dimensions. STSK is based on the activation of one of Q appropriately indexed space-time dispersion matrices within each STSK block duration  $T_B$ . In STSK  $log_2(Q)$ bits index a dispersion matrix selected from among Q available dispersion matrices of size  $N \times T$ , where N is the number of transmit antennas and  $T \leq N$  is the number of columns of the dispersion matrix. The selected dispersion matrix disperses the energy of the input information symbol taken from an *L*-ary PSK or QAM constellation, which is indexed by the remaining bits of the transmitted block [23]. The STSK transmitted signal can be expressed as follows [23]:

$$X_{STSK}(i) = S_1(i) \times \mathbf{0}_{\mathbf{N} \times \mathbf{T}} + \dots + S_q(i) \times \mathbf{A}_q(i) + \dots + S_Q(i) \times \mathbf{0}_{\mathbf{N} \times \mathbf{T}}$$
(1)

where  $S_q(i)$  is the transmitted complex symbol and  $A_q(i)$  is the selected dispersion matrix, which can be represented as:

$$\mathbf{A}_{\mathbf{q}}\left(\mathbf{i}\right) = \begin{bmatrix} a_{1}^{1} & \cdots & a_{1}^{T} \\ \vdots & \ddots & \vdots \\ a_{N}^{1} & \cdots & a_{N}^{T} \end{bmatrix} \in \mathbb{C}^{N \times T}$$
(2)

The zero matrices in (1) are related to the deactivated dispersion matrices, where only one matrix q is activated during each symbol transmission [23]. Every column of the selected matrix is then transmitted from *N*-antenna array at a baud-rate  $T/T_B$ .

Four parameters characterize STSK transmission, including

the number of transmit antennas N, the number of receive antennas M (in a backhaul system N=M), the cardinality of the set of dispersion matrices Q and T. Hence, in the following discourse the specific STSK configurations will be identified by a vector of parameters (N,M,T,Q).

# JNAO Vol. 14, Issue. 2: 2023

The computation of the dispersion matrices has been performed off-line, by following the criterion shown in [24]. Substantially, the pairwise error probability of STSK has been minimized by means of a near-optimal and computationally tractable Genetic Algorithm, applied to a population made of dispersion matrix sets<sup>1</sup>.

STSK can be regarded as an extension and improvement of SM [23]. More specifically, SM can be regarded as a special case of STSK by imposing T=1 and

**ASM** (i) = 0 ··· 1 ··· 0' 
$$\in \mathbb{R}N \times 1$$
 (3) q

where the non-zero element is in the position q of the array. For completeness and for the sake of comparison, the SMUX transmitted symbols vector can be expressed in the following manner:

 $\underline{X}_{SMUX} = IN\underline{S}(i)$  (4) where  $I_N$  is identity matrix and  $\underline{S}(i)$  represents the transmission vector of size  $N \times 1$ . It is interesting to note that the throughput of STSK does not depend on the number of transmit antennas N, as shown in (5). The STSK throughput can be increased by: i) increasing the modulation order L, ii) increasing the number of dispersion matrices Q and iii) decreasing the dispersion matrix duration T. Increasing Q may increase the pairwise error probability as reported in [17], where it was



that O = 4is a satisfacto ry tradeoff between efficiency and performa nce. Thus, it is better to tune the modulatio n order L and T in order to efficientl

suggested

Fig. 1: Small cell backhaul in dense urban environment.

626

y manage the trade-off between diversity and multiplexing.

$$\eta (STSK) = \underline{\qquad} log2 (L) + log2$$

$$(Q) [b/s/Hz] (5) T$$

Furthermore, the throughput of SM logarithmically increases with the number of transmit antennas, as shown in (6), while the throughput of SMUX increases linearly with N, as shown in (7).

$$\eta (SM) = log_2(L) + log_2(N)[b/s/Hz]$$
(6)

$$\eta (SMUX) = Nlog_2(L)[b/s/Hz]$$
(7)

As correctly stated in [23], the augmented diversity of STSK, achieved both at the transmitter and receiver side, comes at the price of potential decrease of throughput with respect to SM that exploits receive diversity only. When compared with SMUX, both STSK and SM achieve lower throughput. However, it should be highlighted that SMUX does not provide any diversity gain against multipath effects, offering multiplexing gain only equal to the number of transmit antennas. STSK is more flexible than SMUX as it can tune different parameters to achieve a trade-off between diversity and multiplexing, while in SM higher throughput can be obtained only by exponentially increasing the number of transmit antennas with а considerable increase of hardware costs.

# B. Description of the mm-wave STSK-based MIMOOFDM transceiver for small cell backhaul

In this paper, we propose to evaluate two MIMOOFDM STSK schemes, which differ in the way the channel coding is applied to the transmitted bit stream.

The first scheme is referred to as *convolutionally*encoded STSK (CESTSK), which is shown in Fig. 2. In the CESTSK scheme, the set of n bits forming the transmitted block are taken from the interleaved output of a convolutional encoder at rate k/n. Therefore, both the  $log_2(Q)$  bits selecting the dispersion matrix and the remaining m bits indexing the  $2^m$ -ary PSK symbol are encoded and interleaved. The convolutionally-encoded STSK matrix columns are then transmitted over P OFDM subcarriers. The corresponding receiver scheme is shown on Fig. 3.

The second scheme is referred to as *Trellis-coded STSK (TCSTSK)*, whose transmitter block

### **JNAO** Vol. 14, Issue. 2: 2023

diagram is shown in Fig. 4 and the receiver structure is shown in Fig. 5. The TCSTSK has been derived by the TCM approach for SM (TCSM) considered by Mesleh *et. al* in [25]. In this scheme, the  $log_2(Q)$  bits selecting the dispersion matrix are uncoded, while the remaining v bits of the block produce a TCM symbol, which is multiplied by the dispersion matrix. The CESTSK scheme is more robust against noise and channel effects, while the TCSTSK scheme gains in terms of throughput efficiency. More precisely, the normalized throughput offered by the two schemes is given as follows:

$$\eta \left( CESTSK \right) = \frac{k(m + \log_2\left(Q\right))}{nT} \left[ b/s/Hz \right]$$
(8)

$$\eta \left(TCSTSK\right) = \frac{v + \log_2\left(Q\right)}{T} \left[b/s/Hz\right]$$
(9)

Both schemes rely on maximum-likelihood detection performed in the frequency domain (ML-FD). One of the main advantages of OFDM-MIMO systems is the possibility of applying the optimum ML detection at the subcarrier level with tolerable computational complexity [23]. Indeed, ISI-free OFDM transmission with cyclic prefix converts a frequency-selective fading channel into P statistically-independent flat-fading channels. Hence in our OFDM-STSK schemes, FD-ML finds the optimum vector ( $q_{optb}k_{opt}$ ) miminizing the following metric [23], where the index i is related to the current signaling period:

$$q_{opt}, k_{opt}) = \min_{q,k} \left\{ \left\| \mathbf{Y}_{\mathbf{p}} \left( \mathbf{i} \right) - \mathbf{H}_{\mathbf{p}} \mathbf{C}_{\underline{\kappa}_{q,k}} \left( i \right) \right\|^{2} \right\}, \\ p = 0, \cdots, P - 1$$
(10)

2

where:

- Y<sub>p</sub> (i) ∈ C<sup>NT×1</sup> is the vectorial stacking of the MIMO-STSK signal received over the p<sup>th</sup> subcarrier;
- $\mathbf{H}_{\mathbf{p}} \in \mathbf{C}^{NT \times NT}$  is the channel matrix related to the  $p^{th}$  subcarrier;
- $\mathbf{C} = [vec(A_1), \cdots, vec(A_Q)] \in \mathbf{C}^{NT \times Q}$ , with vec() being the vectorial stacking operator;

$$\underline{\kappa}_{q,k}(i) = \underbrace{\left[\underbrace{0, \cdots, 0}_{q-1}, \widehat{S}_k, \underbrace{0, \cdots, 0}_{Q-q}\right]}_{\text{Q-q}}, \text{ where } S_k^* \text{ is one of the symbol belonging to the PSK constellation.}$$

•

Finally, given the optimum estimation of the dispersion matrix index (q) and of the encoded transmitted PSKsymbol  $S_k$ , the information bit block is finally decoded, as shown in Fig. 3 and 5.

IV. Mm-wave backhaul channel modeling and link impairments

In this section, the mm-wave backhaul channel modeling will be considered in details, together with the most significant link impairments affecting the system performance.

# A. Small-scale propagation phenomena: multipath fading

MIMO channel capacity is severely limited by transmit and receive spatial correlations [26]. As

#### JNAO Vol. 14, Issue. 2: 2023

discussed in [27], the mm-wave MIMO channel can be modelled using time clusters and spatial lobes. Hence, the statistical spatial channel model (SSCM) used in this work is based on temporal clusters and spatial lobes, as described in [28]. It is proven in [29] that power delay profiles (PDP) at mmWave frequencies are obtained with greater temporal resolution on the order of 2.5 ns and also narrower spatial resolutions on the order of 7° to 10° compared to the channel models for sub-10GHz. This actually shows that temporal clusters are composed of many intra-cluster sub-paths with different random delays as described in [27].

The MIMO channel impulse response [28] can be modelled using a double-directional time invariant model represented as:



Fig. 2: Convolutionally-encoded STSK (CESTSK) transmission scheme for mm-wave backhaul.



Fig. 3: Convolutionally-encoded STSK (CESTSK) receiver scheme for mm-wave backhaul.



Fig. 4: Trellis-encoded STSK (TCSTSK) transmission scheme for mm-wave backhaul.

# C. Three-state channel model

In [4], the probabilistic analyses with respect to the backhaul distance (d) for the three-state channel model are represented as follows:

$$Poutage = max\{0,1 - exp(-a_{out}d + b_{out})\}(15)$$

$$PLOS(d) = \{1 - P_{outage}(d)\}exp(-a_{LOS}d) (16)$$

$$P_{NLOS}(d) = 1 - PLOS(d) - Poutage(d) (17)$$

The parameters used in (15)-(17) have been derived in empirical manner from the NYC measurement campaign, where  $1/a_{LOS}$ =67.1 m,  $1/a_{out}$ =30.0 m. and  $b_{out}$ =5.2. Authors of [4] warmly suggest caution in generalizing these particular parameters in other scenarios, where the outage probability is strictly dependent on the communications environment. However, we think

include a "LOS-dominant" region, whose distance limit is around 46 m., a "NLOS dominant" region extended until 155-160m. Then, increasing the distance beyond 160m, we access the outage region, where the backhaul link is most likely to be unavailable. Indeed, in the outage state, the pathloss is likely to be infinite and hence the destination signal-to-noise ratio is severely degraded. The definition of "small cells" claims that the maximum cell diameter is 200 meters, which exceeds the barrier distance for backhaul link availability shown in Fig. 6 and for this reason it should be regarded as an upper bound on the reachable coverage.

that the threestate assumpt ion will lead to a more accurate and realistic analysis of the backhau 1 perform ance in terms of coverag e. Fig. 6 shows the three probabil ity function s versus d, where three propagat ion regions can be identifie d, which

628

# B. Link performance analysis

First we consider the link performance for a  $2 \times$ 2 MIMO backhaul system, which are shown in Fig. 7 and 8. In these simulations, the clustered multipath has been modeled as described in Section IV-A, while the phase noise PSD has been parametrized using the two masks of [36] and [37] labelled in the inner captions of the figures as phase-noise(1) and phase-noise(2), respectively. The first oscillator is a low-noise SiGe component, part of an RF chip-set for the E-band mobile backhaul application, while the second oscillator is a Voltage Controlled Oscillator (VCO) used to implement a Phase-LockedLoop (PLL) for coherent detection of L-QAM signals, which is tunable in the frequency range from 70.5 to 85.5 GHz. The numerical values in dBc/Hz of the two phasenoise PSDs at the frequencies of 1 MHz and 10 MHz are reported in Table IV.

As shown in Fig.7 and 8, the performance improvement attained by CESTSK compared to CESM and CESMUX is evident at a glance. The impact of phase noise on the link performance looks very modest for both the considered oscillators. It is worth noting that CESM performs

# **JNAO** Vol. 14, Issue. 2: 2023

Additionally, the BER results for the 4×4 MIMO system are shown in Fig. 9 and Fig. 10, which fully confirm the trend observed for the  $2 \times 2$  case, even fostering the improvement yielded by STSK. The flexibility inherent to STSK allows to consider two values for the parameter T, namely: T = 2 and T =4, relaxing diversity and incrementing multiplexing in the first case and vice-versa in the second case. The (4,4,2,4) and (4,4,4,4) CESTSK dramatically outperforms the rest of the assessed techniques in both LOS and NLOS scenarios. It is also worth noting the dramatic performance improvement achieved by CESM and TCSM as compared to lower diversity MIMOs as shown in Fig. 7 and Fig. 8. Indeed, as observed in literature, spatial modulation benefits a lot from receiver diversity, in particular when the multipath channel exhibits correlation.

In the  $4\times4$  MIMO case, the phase noise impact on the BER performance is absolutely irrelevant for STSK, for both the CE and TC systems, and generally the impact of phase noise on the performance is reduced for all assessed techniques due to the averaging of jittering effects observed in [34].

6						
2x2 MIMO						
	Modulation	Coding rate	Q	T   N	et data throughput	"li
CESTSK	QPSK	0.5	4	2	$1 \mathrm{ b/s/Hz}$	avai hl
TCSTSK	QPSK	0.5	4	2	$1.5 \mathrm{ b/s/Hz}$	a
CESM	BPSK	0.5	N.A.	N.A.	$1 \mathrm{ b/s/Hz}$	hen
TCSM	QPSK	0.5	N.A.	N.A.	$2 \mathrm{ b/s/Hz}$	t
CE (TC) SMUX	QPSK	0.5	N.A.	N.A.	2 b/s/Hz	out-o
						serv

 TABLE II: 2x2 MIMO transmission configurations

slightly better than CESMUX both in NLOS and LOS channels. This can be due to the receiver diversity attained by spatial modulation. On the other hand, when considering TCSTSK, we can notice a dramaticallydecreased BER curve as compared to TCSM, in particular when the oscillator of [37] is employed. In general, trellisworse coded STSK performs than convolutionallyencoded MIMO transmission techniques, because the correction capability of Viterbi decoding is not completely exploited, when the bits selecting the dispersion matrices are not encoded.

denoted by  $\gamma$ , is accordingly computed. In this series of simulations, the average BER versus backhaul distance for a given out-of-service probability  $\gamma$ , is evaluated by applying the Baye's theorem in the following manner:

probab ility,

The average BER of (18) has been plotted versus backhaul distance d for the CESTSK and TCSTSK techniques in Fig. 11 and Fig. 12, respectively, under "five 9s" availability requirements. The oscillator with the highest phase-noise PSD of [37], which was denoted as "phase-noise (2)" in the previous section, has been considered in these simulations in order to consider a "worst case" scenario, which is useful to derive a lower bound on the achievable coverage. As shown in Fig. 11 and Fig. 12, STSK offers the best coverage in all the considered situations. In general, the convolutionallyencoded MIMO transmission techniques are more robust than trellis-encoded



techniques due to the fact that in this convolutionally coded systems, the channel

Fig. 7: BER vs.Eb/N0 for 2x2 MIMO small-cell backhaul system: NLOS channel state

coding is applied to the entire transmitted symbol block. The (4,4,2,4) CESTSK represents a good trade-off solution, providing a coverage of about 72 m. with a net spectral efficiency of 1 b/s/Hz. A slightly improved coverage has been provided by the (4,4,4,4) CESTSK of about 77 m., while having half the throughput of that for the (4,4,2,4)CESTSK. A coverage of about 58 m. is provided by (2,2,2,4) CESTSK, which makes it suitable for scenarios where cell-sizes are considerably reduced and cost-effective MIMO systems are desired. On the other hand, the SM and SMUX considered in the simulations generally offer backhaul coverage of 50 m. or less, despite their increased throughput, which makes them not suitable for outdoor applications. It is worth noticing that under the link budget and availability constraints considered in these simulations, the barrier distance of 157 meters highlighted in Fig. 6 is not attained.

Therefore, in order to enhance backhaul coverage, we propose two solutions. The first one forecasts the use of almost linear amplifiers and antenna systems with higher gains, where in this work we have considered the horn antennas of [4]. However, this solution suffers from high monetary cost, energy consumption as well as Base Station size. The second solution is to relax the "five 9s" availability constraint, where due to the burst

## JNAO Vol. 14, Issue. 2: 2023

nature of backhaul traffic in small cellular systems, a continuous service availability may neither be useful nor advisable. Therefore, "four 9s" and "three 9s" availability could be enough for a satisfactory quality-of-service.

Hence, in order to appreciate the effect of relaxing the availability rate, we present the backhaul distances reachable by the different MIMO techniques, while keeping the same requirement of bit-error-rate equal 10-6. These results are summarized by the bar plots of Fig. 13 and 14 for the convolutionally-encoded MIMO trellis-coded techniques and the MIMO techniques, respectively. As expected, relaxing the link availability rate, the achievable backhaul coverage improves for all techniques, but only CESTSK and (4,4,4,4) TCSTSK can offer more than 100 m. of coverage with 99.9 % availability. Additionally, the 4×4 CESM reaches 120 m. of backhaul coverage, but only in the "three 9s" case. Convolutionally-encoded SMUX, despite its high throughput, allows backhaul distances well below 100 m. in all the considered cases.

TABLE V: Link budget parameters for mm-wave smallcell backhaul

Parameter	Numerical value		
$P_{TX}$	-8.5 dBW (inclusive of OBO)		
$g_A$	24.5 dB		
$(G/T)_{RX}$	$24.38 \ dB/K$		
	8.0 dB (NLOS)		
$\sigma_s$	5.8 dB (LOS)		



Fig. 8: BER vs.Eb/N0 for 2x2 MIMO small-cell backhaul system: LOS channel state

D. Notes about computational complexity

A crucial aspect in MIMO signal processing is related to the computational complexity. In Table VI we show the computational complexity of OFDM-STSK FD-ML as well as that of the SM and SMUX techniques detection expressed in terms of the elementary operations required to estimate the symbol block transmitted over each subcarrier. The computational complexity of STSK is slightly increased with respect to that of SM, but consistently reduced when compared with that of SMUX, which becomes intractable when the number of MIMO antennas increases. The complexity of the different techniques is shown in the bar plot of Fig. 15 for different MIMO configurations.

#### VI. Conclusions

In this work, an innovative solution based on STSK and OFDM transmission is proposed for mm-wave smallcell backhaul in dense urban environments, where the presence of the line-ofsight between transmit and receive antennas is not guaranteed. Thanks to diversity exploited efficiently in time and space domain, STSK allows to greatly improve link performance and coverage under hostile propagation conditions compared to the stateof-the-art Spatial Modulation and Spatial Multiplexing. The gain of the STSK against SM techniques is attained at the cost of a reduced throughput and slightly increased computational complexity. In this paper, we have showed that the potential advantages of the STSK outweigh the drawbacks in the considered scenarios.

In our future work we will consider the design of countermeasures against non-linear distortions and phase noise in the STSK-OFDM system for millimeter wave communications. Additionally, we will consider the effect of channel estimation errors on STSK performance, with the consequential assessment of the computational and hardware cost that a robust channel estimator would involve on the backhaul transmission chain.

TABLE VI: Computational complexity of the different MIMO techniques considered for mm-wave small-cell backhaul

MIMO-OFDM technique	Number of elementary operations
STSK	$O\left(NTQ\left(4N+4L\right)\right)  [17]$
SM	$O(8N^2 + 4L(N+1))$ [18]
SMUX	$O(L^N(8N^2+2N))$ [35]



Fig. 9: BER vs.Eb/N0 for 4x4 MIMO small-cell backhaul system: NLOS channel state



Fig. 10: BER vs.Eb/N0 for 4x4 MIMO small-cell backhaul system: LOS channel state



Fig. 11: Average BER vs.backhaul distance d for convolutionally-encoded MIMO techniques and "5 nines" link availability.



Fig. 12: Average BER vs.backhaul distance d for trellis-encoded MIMO techniques and "5 nines" link availability.

References

- M. Agiwal, A. Roy, and N. Saxena, "Next Generation 5G Wireless Networks: A Comprehensive Survey," IEEE Communications Surveys Tutorials, vol. 18, pp. 1617–1655, thirdquarter 2016.
- Y. Niu, Y. Li, D. Jin, L. Su, and A. V. Vasilakos, "A Survey of Millimeter Wave Communications (mmWave) for 5G: Opportunities and Challenges," Wirel. Netw., vol. 21, pp. 2657–2676, Nov. 2015.
- [3] "Technical Report: Technical Requirements for Fixed Radio Systems Operating in the Bands 25.25-26.5 GHz

JNAO Vol. 14, Issue. 2: 2023

and 27.5- 28.35 GHz," Federal Communications Commission, Office of Engineering and Technology, 2013.

- [4] M. R. Akdeniz, Y. Liu, M. K. Samimi, S. Sun, S. Rangan, T. S. Rappaport, and E. Erkip, "Millimeter Wave Channel Modeling and Cellular Capacity Evaluation," IEEE Journal on Selected Areas in Communications, vol. 32, pp. 1164–1179, June 2014.
- [5] B. Farhang-Boroujeny and H. Moradi,
   "OFDM Inspired Waveforms for 5G,"
   IEEE Communications Surveys Tutorials, vol. PP, no. 99, pp. 1–1, 2016.
- [6] "Scenarios and requirements for small cell enhancement for EURTA and E-UTRAN," European Telecommunications Standard Institute (ETSI), 2014.
- [7] X. Ge, S. Tu, G. Mao, C. X. Wang, and T. Han, "5G UltraDense Cellular Networks," IEEE Wireless Communications, vol. 23, pp. 72–79, February 2016.
- [8] V. Dyadyuk, J. D. Bunton, J. Pathikulangara, R. Kendall, O. Sevimli, L. Stokes, and D. A. Abbott, "A Multigigabit Millimeter-Wave Communication System With Improved Spectral Efficiency," IEEE Transactions on Microwave Theory and Techniques, vol. 55, pp. 2813–2821, Dec 2007.
- [9] C. Sacchi, C. Stallo, and T. Rossi, "Space and frequency multiplexing for MM-wave multi-gigabit point-to-point transmission links," in 2013 IEEE Aerospace Conference, pp. 1–10, March 2013.
- [10] P. W. Wolniansky, G. J. Foschini, G. D. Golden, and R. A. Valenzuela, "V-BLAST: an architecture for realizing very high data rates over the rich-scattering wireless channel," in 1998 URSI International Symposium on Signals, Systems, and Electronics, 1998. ISSSE 98., pp. 295–300, Sep 1998.
- [11] I. Frigyes and L. Csurgai-Horvath, "From Gigabit to MultiGigabit: mm Waves in Mobile Networks' Backhaul," in 2009 IEEE Globecom Workshops, pp. 1–6, Nov 2009.
- [12] M. Coldrey, J. E. Berg, L. Manholm, C. Larsson, and J. Hansryd, "Non-line-of-

633

sight small cell backhauling using microwave technology," IEEE Communications Magazine, vol. 51, pp. 78–84, September 2013.

- [13] D. Cvetkovski, T. Halsig, B. Lankl, and E. Grass, "Next generation mm-Wave wireless backhaul based on LOS MIMO links," in 2016 German Microwave Conference (GeMiC), pp. 69–72, March 2016.
- [14] F. Rahman, C. Sacchi, and C. Stallo, "MM-wave LTE-A small-cell wireless backhauling based on TH-IR techniques," in 2015 IEEE Aerospace Conference, pp. 1–9, March 2015.
- [15] Z. Gao, L. Dai, D. Mi, Z. Wang, M. A. Imran, and M. Z. Shakir, "MmWave massive-MIMO-based wireless backhaul for the 5G ultra-dense network," IEEE Wireless Communications, vol. 22, pp. 13– 21, October 2015.
- [16] L. Chen, F. R. Yu, H. Ji, V. C. M. Leung, X. Li, and B. Rong, "A full-duplex selfbackhaul scheme for small cell networks with massive MIMO," in 2016 IEEE International Conference on Communications (ICC), pp. 1–6, May 2016.
- [17] S. Sugiura, S. Chen, and L. Hanzo, "Coherent and Differential Space-Time Shift Keying: A Dispersion Matrix Approach," IEEE Transactions on Communications, vol. 58, pp. 3219–3230, November 2010.
- [18] R. Y. Mesleh, H. Haas, S. Sinanovic, C. W. Ahn, and S. Yun, "Spatial Modulation," IEEE Transactions on Vehicular Technology, vol. 57, pp. 2228–2241, July 2008.
- [19] P. Liu and A. Springer, "Space Shift Keying for LOS Communication at mmWave Frequencies," IEEE Wireless Communications Letters, vol. 4, pp. 121– 124, April 2015.
- [20] K.-C. Huang and Z. Wang, Millimeter Wave Characteristics, pp. 1–31. Wiley, 2011.
- [21] 47, no. 1, pp. n/a–n/a, 2012. RS1005.